



## VHF AND UHF TRANSCEIVERS

### IC-F1000T

VHF transceiver with full keypad

### IC-F1000S

VHF transceiver with simple keypad

### IC-F1000

VHF transceiver without LCD and front keypad

### IC-F2000T

UHF transceiver with full keypad

### IC-F2000S

UHF transceiver with simple keypad

### IC-F2000

UHF transceiver without LCD and front keypad

# Compact, Slim Dimensions IP67 Waterproofing and Full of Useful Features

#### IP67 Waterproof and Dust-tight Protection

The IC-F1000 series has a 24.5mm (0.96 in) slim depth with IP67 waterproof casing. The transceiver can withstand 1m depth of water for 30 minutes. Its dust-tight construction prevents the ingress of powder dust, sand, mud and other objects.

#### Enhanced Emergency with Built-in Motion Sensor

With a built-in motion sensor, the IC-F1000 series can detect its position, state of motion and non-motion and can send an emergency signal. The motion function detects if the transceiver is moving or shaking, for example, during a chase. The lone worker and man down functions are programmable.

#### Easy to Hear in a Noisy Environment

The large 36mm speaker of the transceiver provides clear companded 800 mW\* audio. The built-in BTL amplifier doubles the audio output power and delivers loud and intelligible voice to a radio operator working in noisy environments.

\* Typical with internal speaker

#### Inversion Voice Scrambler

The built-in inversion voice scrambler provides secure conversation. Up to 16 codes are selectable.

#### 14 Hours of Operating Time with Supplied Waterproof Battery

The supplied waterproof Li-ion battery pack, BP-279 (1570mAh typ.), provides 14 hours\* of operating time.

\* Tx:Rx:Standby=5:5:90. Power save function ON.

#### Quiet Stand-by and More

The IC-F1000 series has built-in 2-Tone, 5-Tone, CTCSS and DTCS signaling capabilities for group communication and selective calling.

#### MDC 1200 Compatible

The following MDC features are programmable.

- PTT ID • Emergency (No ACK transmission)
- Radio check (RX only) • Stun/Revive (RX only)
- Transmit status messages (LCD types only)
- 100 alias table (LCD types only)

#### Channel Announcement

When you rotate the channel knob, the radio announces the channel number. Convenient for making radio adjustments without having to look at the radio.

#### Other Features

- 8 DTMF autodial memories
- BIIS PTT ID and emergency call
- "Shift key" function increases number of programmable key assignments
- Surveillance function
- Hands-free operation with optional headset



IC-F2000T

IC-F1000  
(with optional stubby antenna)



Limited functions.

## SPECIFICATIONS

	IC-F1000/S/T	IC-F2000/S/T
<b>GENERAL</b>		
Frequency coverage (MHz)	136–174MHz	335–380MHz (EXP)*1, 400–470MHz (USA/EXP), 450–512MHz (USA), 450–520MHz (EXP)
Number of channels	IC-F1000/F2000 16 channels IC-F1000T/S, F2000T/S	128 channels
Type of emission	16K0F3E*2/11K0F3E	
Channel spacing	12.5/25kHz	
Power supply requirement	7.5V DC nominal	
Current drain (typical)		
Tx High	1.3A	
Rx Max. audio/Standby	330mA (Internal SP)/77mA	300mA (Internal SP)/80mA
Antenna impedance	50Ω	
Operating temperature range	-30°C to +60°C; -22°F to +140°F (Radio specification)	
Dimensions (W×H×D) (Projections not included)	52.2×111.8×24.5mm; 2.06×4.4×0.96 in (With BP-279)	
Weight (approx.)	240g; 8.47oz (With BP-279)	
<b>TRANSMITTER</b>		
Output power	5W, 2W, 1W (Hi, L2, L1)	4W, 2W, 1W (Hi, L2, L1)
Max. frequency deviation	± 5.0kHz/±2.5kHz (Wide/Narrow)	
Frequency stability	±2.5ppm	
Spurious emissions	70dB min.	
FM Hum and noise	46/40dB typ. (Wide/Narrow)	
Audio harmonic distortion	1.0%/1.5% typ. (W/N, AF 1kHz 40% deviation)	
Ext. microphone connector	3-conductor 2.5 (d) mm (1/10")/2.2kΩ	
<b>RECEIVER</b>		
Sensitivity (at 12dB SINAD)	0.25μV typ.	
Adjacent channel selectivity	76/53dB typ. (TIA-603D W/N)	73/56dB typ. (TIA-603D W/N)
	78/71dB typ. (TIA-603A W/N)	74/64dB typ. (TIA-603A W/N)
Spurious response	70dB min.	
Intermodulation	74dB typ.	73dB typ.
Hum and noise	51/45dB typ. (W/N)	49/43dB typ. (W/N)
Audio output power		
Internal SP (With 12Ω load)	800mW typ. (at 5% distortion)	
External SP (With 8Ω load)	400mW typ. (at 5% distortion)	
External speaker connector	2-conductor 3.5 (d) mm (1/8")/8Ω	

Measurements made in accordance with TIA-603.

All stated specifications are subject to change without notice or obligation.

\*1 IC-F2000 Non-LCD version only. \*2 25kHz bandwidth is no longer available for FCC Part 90 licensees for USA versions. Ask your dealer if you need 25kHz bandwidth.

### Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I-C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	-
Dust Blowing	510.5	I
Immersion	512.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard	
Dust & Water	IP67 (Dust-tight and waterproof protection)

Icom, Icom Inc. and Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/or other countries. All trademarks are the properties of their respective holders.

## OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



Battery packs	Type	Capacity	Operating time*
BP-278	Rechargeable Li-ion	1130mAh (min.) 1190mAh (typ.)	10 hours (Approx.)
BP-279	Rechargeable Li-ion	1485mAh (min.) 1570mAh (typ.)	14 hours (Approx.)
BP-280	Rechargeable Li-ion	2280mAh (min.) 2400mAh (typ.)	20 hours (Approx.)

\* Tx: Rx: standby = 5:5:90. Power save function ON.

**RAPID CHARGER**

BC-123S\*1 BC-213

Charges the BP-279 in 2.5 hours (approx.).

**MULTI-CHARGER**

BC-214

Charges up to six BP-279 battery packs in 2.5 hours (approx.).

**CIGARETTE LIGHTER CABLE & POWER SUPPLY CABLE**

CP-23L For use with BC-213

OPC-656 For use with BC-214

\*1 BC-123SA for USA plug. SE for Europe plug. SV for Australia plug.

**SPEAKER-MICROPHONES**

HM-168LWP HM-158LA HM-159LA

**EARPHONE-MICROPHONES**

HM-153LA HM-166LA

**HEADSETS**

HS-94LWP Ear-hook type

HS-95LWP Behind-the-head type

HS-97 Throat type

**PTT SWITCH CABLE & PLUG ADAPTER CABLE**

VS-4LA OPC-2004LA

Either VS-4LA or OPC-2004LA is required when using HS-97.

**CHARGER BRACKET**

MB-130

For use with BC-213

**BELT CLIP**

MB-133

Alligator type

Same as supplied.

### STANDARD ANTENNAS

- FA-SC25V: 136–150MHz
  - FA-SC55V: 150–174MHz
  - FA-SC25U: 400–430MHz
  - FA-SC57U: 430–470MHz
  - FA-SC72U: 470–520MHz
  - FA-SC01U: 350–400MHz
  - FA-SC02U: 330–380MHz
- CUT ANTENNAS**
- FA-SC61VC: 136–174MHz
  - FA-SC61UC: 380–520MHz
- HIGH GAIN ANTENNAS**
- FA-SC62V: 150–160MHz
  - FA-SC63V: 155–165MHz

### STUBBY ANTENNAS

- FA-SC26VS: 136–144MHz
  - FA-SC27VS: 142–150MHz
  - FA-SC56VS: 150–162MHz
  - FA-SC57VS: 160–174MHz
  - FA-SC26US: 400–450MHz
  - FA-SC73US: 450–490MHz
- CHARGER ADAPTER**
- AD-130
- AD-130 charger adapter is supplied with the BC-214.

**Supplied accessories:** (May differ or not supplied, depending on version)

- Battery pack, BP-279
- Desktop charger, BC-213
- AC adapter, BC-123S
- Belt clip, MB-133
- Antenna



The "3D GENUINE Icom label" is attached to the rear chassis under the battery. Check the Icom website for details: <http://www.icom.co.jp/world/genuine-info/>

## Icom Inc.

1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

[www.icom.co.jp/world](http://www.icom.co.jp/world)

## Count on us!

Your local distributor/dealer:

### Icom America Inc.

12421 Willows Road NE,  
Kirkland, WA 98034, U.S.A.  
Phone: +1 (425) 454-8155  
Fax: +1 (425) 454-1509  
E-mail: [sales@icomamerica.com](mailto:sales@icomamerica.com)  
URL: <http://www.icomamerica.com>

### Icom (Europe) GmbH

Communication Equipment  
Auf der Krautweide 24  
65812 Bad Soden am Taunus, Germany  
Phone: +49 (6196) 76685-0  
Fax: +49 (6196) 76685-50  
E-mail: [info@icom-europe.com](mailto:info@icom-europe.com)  
URL: <http://www.icomeurope.com>

### Icom France s.a.s.

Zac de la Plaine,  
1 Rue Brindejonc des Moulinais, BP 45804,  
31505 Toulouse Cedex 5, France  
Phone: +33 (5) 61 36 03 03  
Fax: +33 (5) 61 36 03 00  
E-mail: [icom@icom-france.com](mailto:icom@icom-france.com)  
URL: <http://www.icom-france.com>

### Icom Canada

Glenwood Centre #150-6165  
Highway 17A, Delta, B.C.,  
V4K 5B8, Canada  
Phone: +1 (604) 952-4266  
Fax: +1 (604) 952-0090  
E-mail: [info@icomcanada.com](mailto:info@icomcanada.com)  
URL: <http://www.icomcanada.com>

### Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"  
Bajos A 08174, Sant Cugat del Valles,  
Barcelona, Spain  
Phone: +34 (93) 590 26 70  
Fax: +34 (93) 589 04 46  
E-mail: [icom@icomspain.com](mailto:icom@icomspain.com)  
URL: <http://www.icomspain.com>

### Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,  
Clayton, VIC 3168 Australia  
Phone: +61 (03) 9549 7500  
Fax: +61 (03) 9549 7505  
E-mail: [sales@icom.net.au](mailto:sales@icom.net.au)  
URL: <http://www.icom.net.au>

### Icom Brazil

Rua Itororó, 444 Padre Eustáquio  
Belo Horizonte MG,  
CEP: 30720-450, Brazil  
Phone: +55 (31) 3582 8847  
Fax: +55 (31) 3582 8987  
E-mail: [sales@icombrasil.com](mailto:sales@icombrasil.com)

### Icom (UK) Ltd.

Blacksole House, Altira Park,  
Herne Bay, Kent, CT6 6GZ, U.K.  
Phone: +44 (0) 1227 741741  
Fax: +44 (0) 1227 741742  
E-mail: [info@icomuk.co.uk](mailto:info@icomuk.co.uk)  
URL: <http://www.icomuk.co.uk>

### Shanghai Icom Ltd.

No.101, Building 9, Caifuxingyuan Park,  
No.188 Maoting Road, Chedun Town,  
Songjiang District, Shanghai, 201611, China  
Phone: +86 (021) 6153 2768  
Fax: +86 (021) 5765 9987  
E-mail: [bjicom@bjicom.com](mailto:bjicom@bjicom.com)  
URL: <http://www.bjicom.com>